

TCM-6630

36x Zoom H.264 IP D/N Outdoor Speed Dome

Hardware User's Manual

Ver. 2011/8/30



Table of Contents

0. Precautions	4
1. Introduction	5
Package Contents	5
Features and Benefits	6
Safety Instructions	8
Physical description	9
2. Installation Procedure	14
Installing Speed Dome Cover	14
1) Remove the Plastic Protection cap	14
2) Apply Lubricant to clear cover	14
3) Attach clear cover to speed dome	15
Connecting cables.....	16
Network Connection	18
Mounting Options for Speed Dome	19
Wall	19
Corner.....	22
Pole.....	24
Ceiling.....	26
3. Appendix	27
OSD Menu Notes (On Screen Display)	27
OSD Display Format	27
OSD Setup Menu	27
Configuration Menu.....	30
Default Camera	30
Backlight	30
FOCUS	31

APERTURE.....	31
AE MODE	32
WBC MODE	32
ID DISPLAY.....	33
SETUP MENU	34
TITLE DISPLAY	36
TITLE SETTING.....	37
ALARM SETTING	37
HOME SETTING.....	39
SEQUENCE	40
AUTOPAN	42
CRUISE.....	44
IR FUNCTION (Removable IR Cut).....	44
WDR SETTING.....	45
PRIVACY.....	46
TIME FUNCTION.....	48
EXIT OSD	49
Product Specification.....	50

4. Accessing Camera

52

If you have DHCP server / router in your network:	52
If you do <i>NOT</i> have DHCP server / router in your network:	52

0. Precautions

Read these instructions

You should read all the safety and operating instructions before using this product.

Heed all warnings

You must adhere to all the warnings on the product and in the instruction manual. Failure to follow the safety instruction given may directly endanger people, cause damage to the system or to other equipment.

Servicing

Do not attempt to service this video device yourself as opening or removing covers may expose you to dangerous voltage or other hazards. Refer all servicing to qualified service personnel.

Trademarks

All names used in this manual are probably registered trademarks of respective companies.

Liability

Every reasonable care has been taken during the writing of this manual. Please inform your local office if you find any inaccuracies or omissions. We cannot be held responsible for any typographical or technical errors and reserve the right to make changes to the product and manuals without prior notice.

FCC/CE Regulation

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the users will be required to correct the interference at their own expense.

1. Introduction

Package Contents

TCM-6630



Power Adaptor



Network Cable



Power, Audio and Video Cable



Alarm Cable



Waterproof Rubber Sleeve & Mounting Kit



Product CD



Accessories (Lubricant / Screws)



Warranty Card



Features and Benefits

The IP High Speed Dome is designed to deliver superb performance and durability with an intelligent and stylish housing. It also provides a reliable real time images with outstanding image quality (D1, 720x480). It can compress and transmit real time images with outstanding image quality (30 FPS @ D1, 720 x 480 or 720 x 576) through a standard TCP/IP network. This camera is your best choice to build an intelligent IP surveillance system.

High Speed Pan-Tilt and Zoom

This High Speed Dome is available:

36x MODEL: 36x optical zoom plus 12x digital magnifier/D&N/WDR

Precise and Accurate Tracking

Scheduling function, a special feature, enables users to program a preset point or patrol sequence. This IP high speed dome provides variable pan/tilt speed ranging from a fast patrol of 400° per second to a slow ramble of 5° per second with 0.225° pan accuracy for fast and accurate tracking ability. The 360° endless rotation and -10°~190° tilt travel makes tracking the object passing directly beneath the dome very easy. Maximum 256 preset points can be programmed for precise location of target areas, and you may also define 8 patrol sequences, 4 auto-pan sets and 1 cruise rotation for the camera to operate automatically.

Day/Night Features

Mechanically Removable IR cut filter ensures 24 hours operation.

Low-Light Application

Digital Slow Shutter and Electronic Shutter functions are provided for clear and high quality image. The minimum illumination is 0.01 Lux.

Perfect Contrast Solution for High Image Quality

Wide Dynamic Range function is an important feature incorporated to fit your needs

Privacy Mask for Privacy Protection

There are up to 24 configurable privacy zones. This is specially designed to avoid any intrusive monitoring at specific regions.

H.264/MPEG-4/MJPEG Triple Codec Dual Streaming

This device supports 3 compression formats, H.264, MPEG-4 and MJPEG. It brings superior image quality at 30 frames per second up D1 resolution (720 x 480 pixels).

Built-in Hardware Motion Detection

No more external motion sensors are required. You may assign up to 3 video motion detection areas. By tuning the object size and sensitivity, it will reliably detect objects passing through in view. Hardware motion detection also offers better sensitivity and faster response time than software motion detection.

Powerful Bundled Surveillance Software

To extend the capabilities of the IP Camera, a powerful surveillance program is included in the package for free. Users can easily use an existing PC as a digital video recorder. Scheduled recording and manual recording keep every important video recorded in the local hard disk. Reliable and accurate motion detection with instant warning enables immediate response in every condition. Quick and simple search and playback function lets you easily find the images and video you want.

Software Development Kit Support

This IP Camera can be integrated or controlled by applications from third party software developers. Software developers can save considerable efforts by using our Streaming Library or ActiveX control. Please contact us for details on integration support.

Digital Time Code Embedded

The "Digital Time Code Embedded" function records video time in the video stream. Therefore, each image frame is marked with its original recording time. It is very useful when users want to find the video at an exact time or between a certain time intervals.

Safety Instructions

Don't use the power supply with other voltages

This device is likely to be damaged or damage other equipments / personnel, if you use a power supply with different voltage than the one included with this device. All warranty of this product will be voided in the situations above.

Cleaning

Disconnect this video product from the power supply before cleaning.

Attachments

Do not use attachments not recommended by the video product manufacturer as they may cause hazards.

Water and Moisture

Do not use this video product near water, for example, near a bathtub, washbowl, kitchen sink, or laundry tub, in a wet basement, or near a swimming pool and the like.

Servicing

Do not attempt to service this video product yourself as opening or removing covers may expose you to dangerous voltage or other hazards. Refer all servicing to qualified service personnel.

Damage Requiring service

Disconnect this video product from the power supply immediately and refer servicing to qualified service personnel under the following conditions.

- 1) When the power-supply cord or plug is damaged
- 2) If liquid has been spilled, or objects have fallen into the video product.
- 3) If the video product has been directly exposed to rain or water.
- 4) If the video product does not operate normally by following the operating Instructions in this manual. Adjust only those controls that are covered by the instruction manual, as an improper adjustment of other controls may result in damage, and will often require extensive work by a qualified technician to restore the video product to its normal operation.

Safety Check

Upon completion of any service or repairs to this video product, ask the service technician to perform safety checks to determine if the video product is in proper operating condition.

Physical description



1) Reset Button

Step 1: Switch off IP device by disconnecting the power cable

Step 2: Press and continue to hold the Reset Button (with a sharp tipped object, like a pen.)

Step 3: **Reconnect the power cable while continuing to hold the reset button for 20 seconds.** By this time the reset to default operation is already completed. You may then release the reset button. This length of time fluctuates slightly with the environment. The Power LED light will come back on and stay on after a few more seconds. The unit will start up with factory default settings automatically.


2) Dome Control Protocol

To control PTZ action of this Speed Dome, the control protocol of your software must match the one used by the Speed Dome Camera. Use these switches to set your dome control protocol and the baud rate. Refer to table below and turn the arrow to choose a protocol for your speed dome.

Switch No.	Protocol	Baud Rate
00	VCL	9600
01	Pelco D	2400
02	Pelco P	4800
04	Chiper	9600
05	Philips	9600
07	DSCP	9600
08	AD422	4800
09	DM P	9600
11	Pelco D	4800
12	Pelco D	9600
13	Pelco P	2400
14	Pelco P	9600
15	JVC	9600
21	Kalatel-485	9600
22	Kalatel-422	4800

Default setting is 07 DSCP (Dynacolor) baud rate 9600

To select a protocol, turn the switch to the proper number. For example, Pelco D at baud rate 2400 is listed under switch No. 1. The ID switch should be set as below:




3) Ethernet Port


The IP device connects to the Ethernet via a standard RJ45 connector. Supporting NWAY, this IP device can auto detect the speed of local network segment (10Base-T/100Base-TX Ethernet).

4) 22 pin connector for Power / Audio In / Audio Out / Video Out / DIO

This 50 cm cable consolidates all these wires to a single connection.




Power Input / Audio In / Audio Out / Video Out are pre-connected. For DIO, there is a separate cable that you may insert into the 22 pin connector. Please reference the table below for pin definitions




Pin	Definition	Cable
1	AC 24-1/DC(+)	20 AWG
2	ALM NC	
3	AC 24-1/DC(-)	20 AWG
4	ALM NO	
5	FG	20 AWG
6	ALM COM	
7	MIC +	24 AWG
8	SPK +	
9	MIC -	
10	SPK -	
11	ISOG	
12	ALM-1	
13	ALM-2	
14	ALM-3	
15	ALM-4	
16	ALM-5	
17	ALM-6	
18	ALM-7	
19	ALM-8	
20	ALM GND	
21	VGND	24 AWG
22	Video	


Please see the graph below on how to insert terminals to connector housing.



Insert the terminal into the pin holes on the connector housing, with the hook outward, as indicated in the figure.




To unlock the terminal, press the hook, as indicated in the figure, with a proper tool and pull it out gently.



5) Dome ID Setting

Use the switch to change your speed dome ID by turning the arrow to change each digit to the desired number. For instance, if the Speed dome ID is 123, the ID switch should be set as below:



NOTE: If controlling through an ACTi decoder via analog means such as a keyboard or DVR, no two speed domes should be given the same ID or communication conflict may occur. When controlled only through Ethernet and software (without the use of an ACTi hardware decoder), the dome ID setting may be ignored.



6) Communication Switch Setting

The table below shows the function of each pin within the Communication Switch

Communication Switch		Pin 1	RS-232 Setting (Reserved)
	Pin 2	Termination	
	Pin 3	Line Lock	
	Pin 4	System Initialization (for upgrade)	
	Pin 5	Reserved	
	Pin 6		

RS-232 is reserved for internal use only; The Pin 3 and Pin 4, they are used for termination and Link Lock adjustment respectively. The Pin 5 is mainly used for return to factory default of camera setting.

7) Suspension Loop

This metal cable loop is used to suspend Speed dome from mounting accessories during installation so that it does not fall down by slipping.

2. Installation Procedure

Installing Speed Dome Cover

1) Remove the Plastic Protection cap

Remove the plastic protection cap from the speed dome unit.



2) Apply Lubricant to clear cover

Apply lubricant included in package to dome cover rubber sleeve. This helps ease installation



3) Attach clear cover to speed dome

There are a few micro-steps involved here.

First you need to find the plastic stud by the side of dome cover. Insert that into one of the slots at the side of speed dome.



Secondly, there are two metal screws at the sides of the dome cover. Use a flat headed screwdriver and unscrew them. Unscrewing will extend them outwards, securing the dome cover.



Lastly use the small screw included in package to lock the dome cover into position.



Connecting cables

When installing, please note that you should string the cable through the accessories, the rubber waterproof sleeve, the mount kit and then into the ports. Please see image below for sequence.



There are three locking areas on the mount kit. Put it on top of the speed dome, then rotate it into position.




Once it is rotated into position, you may use the other larger screw to keep it in place.



Network Connection

Follow the diagram below to connect the IP high speed dome to the respective devices.



Mounting Options for Speed Dome

Wall

Heavy Duty Wall Mount

PMAX-0309



Heavy Duty Wall Mount + Junction Box

PMAX-0309 + PMAX-0700



Gooseneck Wall Mount - Raised

PMAX-0307



Gooseneck Wall Mount - Flat

PMAX-0306



Gooseneck Wall Mount + Junction Box

PMAX-0306 + PMAX-0700



Corner

Heavy Duty Corner Mount

PMAX-0309 + PMAX-0402



Heavy Duty Corner Mount + Junction Box

PMAX-0309 + PMAX-0402 + PMAX-0700



Gooseneck Corner Mount

PMAX-0306 + PMAX-0402



Gooseneck Corner Mount + Junction Box

PMAX-0306 + PMAX-0402 + PMAX-0700



Pole

Heavy Duty Pole Mount

PMAX-0309 + PMAX-0502



Heavy Duty Pole Mount + Junction Box

PMAX-0309 + PMAX-0700 + PMAX-0502



Gooseneck Pole Mount

PMAX-0306 + PMAX-0502



Gooseneck Pole Mount + Junction Box

PMAX-0306 + PMAX-0700 + PMAX-0502



Ceiling

Pendant Mount

PMAX-0109



Pendant Mount + Junction Box

PMAX-0108 + PMAX-0700




**** If your camera need to be located far below the mounting point, please use PMAX-0104 extension tube.**

3. Appendix

OSD Menu Notes (On Screen Display)

OSD Display Format

The information shown on the screen are described in terms of OSD display, position and function description in the table below.



Position	Function	OSD Display	Description
1	Focus Modes	A	Auto Focus Mode
		M	Manual Focus Mode
2	Backlight	X	Back Light Compensation OFF
		B	Back Light Compensation ON
3	Alarm	ALARM	Alarm Message
4	Zoom Ratio	×1	Present Zoom Ratio (Optical Zoom(Digital Zoom))
5	Title	<ul style="list-style-type: none"> Maximum 20 characters for each title. 16 sets of title are available. 	
6	Camera ID	Show the camera ID	

OSD Setup Menu

The OSD setup menu structure is listed separately in the following section. The star symbol indicates the factory default.

➤ TCM-6630:

Item	Layer 1	Layer 2	Layer 3	Default	
DEFAULT CAMERA	<ON>, <OFF>			ON	
BACKLIGHT	ON	BLC Level <00> ~ <100>			
	OFF			☆	
FOCUS	AUTO	Focus Length <1cm>, <10cm>, <30cm> <1m>		10 cm	
	MANUAL	<01> ~ <08>			
APERTURE	AUTO			☆	
	MANUAL	H APERTURE <00> ~ <31> V APERTURE <00> ~ <31>			
AE MODE	AUTO	IRIS OFFSET <00> ~ <99>		50	
	SHUTTER	SHUTTER SPEED <1/2> ~ <1/30000>			
	IRIS	IRIS <00> ~ <09>			
	AGC	AGC <00> ~ <05>			
WBC MODE	AUTO			☆	
	MANUAL	R Gain <00> ~ <99> B Gain <00> ~ <99>			
ID DISPLAY	<ON>, <OFF>			ON	
SETUP MENU	FLIP	<IMAGE>(K model only), <M.E.>, <OFF>		OFF	
	ZOOM SPEED	<FAST>, <SLOW>		Slow	
	SPEED BY ZOOM	<ON>, <OFF>		OFF	
	AUTO CALI.	<ON>, <OFF>		OFF	
	DIGITAL ZOOM	<1> ~ <12>, <OFF>		OFF	
	SLOW SHUTTER (K model only)	<1/2> ~ <1/60> Sec. (NTSC) <1/1.5> ~ <1/50> Sec. (PAL)		1/30	
	ANGLE ADJUSTER	ADJUST MIN ANGLE			00
		ADJUST MAX ANGLE			90
	RESET	RESET			
	RESET	YES			
EXIT					
TITLE DISPLAY	<ON>, <OFF>			OFF	
TITLE SETTING	<01> ~ <16>			01	
ALARM SETTING	ALARM PIN	<1> ~ <8>		1	
	ALARM SWITCH	<ON>, <OFF>		OFF	
	ALARM TYPE	<N.O.>, <N.C.>		N.C.	
	ALARM ACTION	PRESET			☆
		SEQUENCE			
		AUTOPAN			
		CRUISE			
	PRESET POINT SEQUENCE LINE	<001> ~ <256>			001
	AUTOPAN LINE	<1> ~ <8>			
	CRUISE LINE	<1> ~ <4>			
DWELL TIME	<001> ~ <127> Sec., ALWAYS			ALWAYS	
EXIT	YES				
HOME SETTING	HOME FUNC.	<ON>, <OFF>		OFF	
	SELECT MODE	PRESET		☆	
		SEQUENCE			

Item	Layer 1	Layer 2	Layer 3	Default	
		AUTOPAN			
		CRUISE			
	PRESET POINT SEQUENCE LINE AUTOPAN LINE CRUISE LINE	<001> ~ <256> <1> ~ <8> <1> ~ <4> <1>		001	
	RETURN TIME	<001> ~ <128> Min.		001	
	GO	ENTER			
	EXIT	YES			
	SEQUENCE	SEQUENCE LINE	<1> ~ <8>		1
SEQUENCE POINT		<01> ~ <32>		01	
PRESET POS.		<001> ~ <255>, <END>		001	
SPEED		<01> ~ <15>		01	
DWELL TIME		<000> ~ <127> Sec.		000	
RUN SEQUENCE		ENTER			
EXIT					
AUTOPAN	AUTOPAN LINE	<1> ~ <4>		1	
	START POINT	<TO FIND>, <TO SAVE>			
	END POINT	<TO FIND>, <TO SAVE>			
	DIRECTION	<RIGHT>, <LEFT>		Right	
	SPEED	<01> ~ <04>		01	
	RUN AUTOPAN	ENTER			
	EXIT				
CRUISE	RECORD START				
	RECORD END				
	RUN CRUISE				
	EXIT				
IR FUNCTION (K model only)	AUTO	THRESHOLD	<LOW>, <MID>, <HI>	LOW	
		IR COLOR	<B/W>, <COLOR>	B/W	
		EXIT			
	ON				
WDR SETTING (K model only)	WDR SWITCH	<ON>, <OFF>		OFF	
	WDR FUNCTION	AUTO		☆	
		MANUA L	RATIO LEVEL <000>~<128>		
			SHUTTER LEVEL <000>~<128>		
			IRIS OFFSET <000>~<128>		
	EXIT				
PRIVACY (K model only)	PRIVACY SWITCH	<ON>, <OFF>		OFF	
	SHADE	<BLACK>, <WHITE>, <GRAY>		Gray	
	SET MASK	<1> ~ <8>	H CENTER <000> ~ <256> V CENTER <000> ~ <256> H SIZE <000> ~ <127> V SIZE <000> ~ <127>		
	MASK CLEAR+RESET	<01> ~ <08>		01	
	MASK DISPLAY	<FIRST>, <LAST>		First	
	EXIT	YES			
TIME	TIME DISPLAY	<ON>, <OFF>		OFF	
	SET YEAR				

Item	Layer 1	Layer 2	Layer 3	Default
	SET MONTH			
	SET DAY			
	SET HOUR			
	SET MINUTE			
	EXIT+SAVE			
EXIT OSD	YES			

Configuration Menu

The detailed functions and parameter settings of your high speed dome can be set by the OSD (On Screen Display) menu with a control program. The functions in OSD menu are described in the following sections.

36x MODEL

MAIN PAGE 1	
DEFAULT CAMERA	OFF
BACKLIGHT	OFF
FOCUS	AUTO
APERTURE	AUTO
AE MODE	AUTO
WBC MODE	AUTO
ID DISPLAY	ON
SETUP MENU	ENTER

Default Camera

The "DEFAULT CAMERA" is used to restore the camera settings (e.g. Backlight/Focus/AE/WBC/Aperture). Once any one of the items is modified, the setting will become <OFF> automatically. Select <ON> for this item to recall the mentioned camera parameters.

Backlight

The Backlight compensation function prevents the center object from being too dark in surroundings where excessive light is behind the center object.

The Backlight Compensation Level ranges from 000 to 100.

	BLC LEVEL	
LEVEL		20
EXIT		YES



NOTE: If this function is enabled, the WDR function will be disabled automatically.

FOCUS

Automatically adjusts the focus position to maximize the high frequency content of the picture in a center measurement area, taking into consideration the high luminance and strong contrast components. The focus of the dome camera can be operated in two modes: Manual Focus mode and Auto Focus mode. Different settings for various models are described as follows.

◆ AUTO

The optimum focus is achieved by the internal digital circuit. Users can adjust the minimum auto focus range for some special conditions; the options are <1cm>, <10cm>, <30cm> and <1m>.

◆ MANUAL

In this focus mode, users can adjust the lens focus manually.

	FOCUS LENGTH	
TURNING VALUE		10CM
EXIT		YES

APERTURE

Sharpness is the subjective evaluation of detail in the picture. With this "APERTURE" function, users can adjust the enhancement of the edges of objects in the picture. When shooting text, this function may help by making them sharper and achieve a better image. There are 32 levels of adjustment, the options are <00> ~ <31>, <00> represents "no enhancement".

◆ AUTO

The dome camera will assign a proper aperture value automatically for camera to achieve a better image.

◆ **MANUAL**

Select this item if you want to adjust aperture value manually. Higher value enhances the incident ray of camera.

APERTURE MENU	
H APERTURE	15
V APERTURE	15

AE MODE

The exposure is the amount of light received by the image sensor and is determined by how wide you open the lens diaphragm (iris adjustment), by how long you keep the sensor exposed (shutter speed), and other exposure parameters. With this item, users can define how the Auto Exposure (AE) function works.

◆ **AUTO**

In this mode, the camera's Shutter, IRIS and AGC control function work automatically to compensate the light exposure of image sensor for consistent video output level. IRIS OFF SET is used to set the level of IRIS variation.

◆ **SHUTTER**

With this option, the SHUTTER priority is higher than IRIS and AGC; IRIS and AGC circuit will function automatically in cooperating with SHUTTER to get consistent exposure.

◆ **IRIS**

With this option, the IRIS priority is higher than SHUTTER and AGC; SHUTTER and AGC circuit will function automatically in cooperating with IRIS to get consistent exposure. If the IRIS is modified manually, the action of exposure compensation depends on the AGC circuit.

◆ **AGC**

With this option, the AGC priority is higher than SHUTTER and IRIS; SHUTTER and IRIS circuit will function automatically in cooperating with AGC to get consistent exposure. If AGC is adjusted manually, the exposure compensation depends on the changing of IRIS.

WBC MODE

A digital camera needs to find reference colour temperature, which is a way of measuring the quality of a light source, for calculating all the other colours. The unit for measuring this ratio is in

degree Kelvin (K). You can select one of the White Balance Control modes according to the condition. The following table shows the colour temperature of some light sources.

Light Sources	Color Temperature in K
Cloudy Sky	6,000 to 8,000
Noon Sun and Clear Sky	6,500
Household Lighting	2,500 to 3,000
75-watt Bulb	2,820
Candle Flame	1,200 to 1,500

◆ **AUTO**

In this mode, white balance works within its colour temperature range and calculates the best-fit white balance.

◆ **MANUAL**

In this mode, users can change the White Balance value manually; adjustable R gain and B gain range from 0 to 99.

WBC MENU	
R GAIN	50
B GAIN	50

ID DISPLAY

Users are allowed to choose whether the dome ID will be displayed on monitor to identify the domes.

◆ **ON**


Display the ID address of the selected dome on the right bottom of the monitor screen.

◆ **OFF**

Hide the ID address of the selected dome.


SETUP MENU

Users can adjust camera lens model parameters under SETUP MENUs. Depending on the model of dome cameras, the SETUP MENUs are different.



◆ FLIP (IMAGE/ME/OFF)

User can track an object continuously when it passes through under dome camera with setting Flip to IMAGE (digital flip) or M.E. (mechanical flip).



IMAGE

IMAGE represents digital IMAGE FLIP, enables users to keep tracking object seamlessly and no delay occurs in comparing with mechanical flip.



NOTE: The Privacy Mask function will be automatically disabled if the Image Flip function is enabled, and “Masking will be disabled” will be displayed on the screen.

M.E.

The item is a standard mechanical operation. As the dome tilts 90°, it will pan 180°, then continuing tilt to keep tracking object.

OFF

Select this item to disable the flip function.



NOTE: The speed dome will only be able to tilt 90°, or -10° ~ 100° with angle adjuster adjustments.

◆ **ZOOM SPEED**

This item is used to set the zoom speed for operating the dome camera.

For this model, the options are <FAST> and <SLOW> (default).

◆ **SPEED BY ZOOM**

If the item is set to <ON>, the pan/tilt speed will be adjusted by internal algorithm when zooming automatically. The larger zoom ratio leads the lower rotation speed.

◆ **AUTO CALIBRATION**

There are one horizontal and one vertical infrared rays check points in each dome. When the dome camera position may be moved during installation or maintenance, the relative distance between the original set point and the check point has been changed. Enable the Auto Calibration function, the dome will automatically detect that and reset the point back to the original position.

◆ **DIGITAL ZOOM**

With this item, users can enable or disable the 12x Digital Zoom. The Digital Zoom activate after the full Optical Zoom level is reached.



NOTE: The difference between optical and digital zoom is that optical zoom uses the lens within the camera to draw the image closer via zoom in or out to achieve the desired effect. Optical zoom remains the same and the full resolution of the zoomed image quality. On the other hand, Digital zoom takes a portion of image and expands that image to the full size of the image; however the image quality will be reduced.

Digital zoom ration is adjustable from <1> to <12>.

◆ **SLOW SHUTTER**

The shutter speed determines how long the image sensor is exposed to light. To see clear image in a dark environment, enable this function and select a slower shutter speed.

The shutter speed is adjustable on TCM-6630. With the slowest shutter speed, users can see objects in a dark environment under 0.2 lux; or see a smooth video image with a higher shutter speed. The options are from <1/2> to <1/60>.

◆ **ANGLE ADJUSTER**

The item is for adjusting the camera view angle. The ranges of view angle are changed in different FLIP mode: the angle ranges from -10° to +100° with ME FLIP and FLIP OFF modes, and from -10° ~ +190° with IMAGE FLIP mode. With IMAGE FLIP function, users are able to adjust the view angle from -10° ~ +190° to catch the true horizontal line.

ANGLE ADJUSTER	
ADJUST MIN ANGLE	-10 DEG
ADJUST MAX ANGLE	100 DEG
EXIT+SET	YES

◆ **STABILIZER (36x Model Only)**

With the Image Stabilizer Function, the speed Dome Camera can capture images that would otherwise be blurred due to the vibration. The built-in electronic compensation filters out the vibrations of up to 80% movement at 10Hz, as caused by wind and other environmental conditions. Its various detection mode ensures total detection for all types of environment. If the function is activated, users could select the frequency range of either 10Hz or 5Hz.

◆ **RESET**

Select this item to reset all the camera parameters of SETUP MENUs to the factory default.

◆ **EXIT**

Exit the SETUP MENU1 and go back to MAN MENU.

TITLE DISPLAY

Users are allowed to name a certain view area and display its title for easy recognition. At this item, users can choose to display or not to display the titles set in advance.

◆ **ON**

A title set for certain view will be displayed when the dome back to the view area.

◆ **OFF**

When the TITLE DISPLAY is set <OFF>, no title will be displayed on the screen even titles are set in advance.

TITLE SETTING

Up to 16 zone titles can be set with maximum 20 characters for each title; two mask zones are allowed to set in a view area. Users can name the zone titles with privacy mask ID numbers for future recognition.



NOTE: For **TCM-6630**, the available area for setting privacy mask is restricted within tilt angle 45°.

Follow the steps to set a camera title.

- (1) Operate speed dome to certain view area where you want to set a title for it.
- (2) Turn on OSD and select <TITLE SETTING>.
- (3) Select a number to indicate the view area.
- (4) Press <ENTER> to go into editing mode.

TITLE SETTING: 01										
0	1	2	3	4	5	6	7	8	9	EXIT
A	B	C	D	E	F	G	H	I	J	SAVE
K	L	M	N	O	P	Q	R	S	T	LEFT
U	V	W	X	Y	Z	:	/	.	,	RIGHT
[]	+	?	-						DELETE
TITLE:										
ABC										

- (5) Choose a character with direction keys and then press <ENTER> to input.
 Example: <A> <ENTER>, <ENTER>, <C> <ENTER>
 TITLE: ABC
- (6) To delete entered characters, move the cursor to <LEFT> or <RIGHT> and press <ENTER> to select a character in entry field, then move the cursor to <DELETE> and press <ENTER> to delete the selected character.
- (7) When the setting is completed, move the cursor to <SAVE> and press <ENTER> to save.

ALARM SETTING

The integrated high speed dome provides eight alarm inputs and two alarm outputs (N.O. and N.C.) to connect alarm devices. With this function, dome will cooperates with alarm system to catch the event images. For wiring, please refer to the installation guide and/or qualified service personnel. Alarm parameters can be set on this page.

ALARM SETTING	
ALARM PIN	1
ALARM SWITCH	OFF
ALARM TYPE	N.C.
ALARM ACTION	
PRESET	
PRESET POINT	001
DWELL TIME	ALWAYS

◆ **ALARM PIN**


The dome provides 8 alarm inputs and 2 outputs (1 x N.O. and 1 x N.C.). Select an alarm connector which you want to set its alarm-related parameters with this item, and then set its alarm-related parameters in Alarm Setting menu.

◆ **ALARM SWITCH**

The item is used to enable or disable the selected alarm pin function.

◆ **ALARM TYPE**

There are two kinds of alarm types: Normal Open and Normal Close, which are illustrated as below. Select an alarm type that corresponds with the alarm application.



◆ **ALARM ACTION**

Select one of these modes that choose a kind of actions that should be executed when an alarm is triggered. The alarm actions can be set to execute the preset position, sequence, auto-pan or cruise function.

◆ **PRESET**

Select a preset point where the dome should go when an alarm pin is triggered.

SEQUENCE

Select a sequence line that the speed dome camera should execute when alarm pin is triggered. The Sequence line should be defined prior in SEQUENCE setup menu.

AUTOPAN

Select an auto-pan line that the dome camera should execute when alarm pin is triggered. The Auto-pan line can be defined in setup AUTOPAN menu.

CRUISE

Select a cruise line that the speed dome camera should execute when alarm pin is triggered. The Cruise line can be defined in CRUISE setup menu.

◆ DWELL TIME

The DWELL TIME is the duration of executing ALARM ACTION: Preset or Sequence. When alarm takes place, the dome will go to the preset position or execute sequence function and stay at each sequence point for a period of time (1~127 seconds). If select <Always>, the dome will go to the preset position and stay there until alarm condition is released or users rotate the dome.



NOTE: The DWELL TIME is only accessible when selecting ALARM ACTION: Preset or Sequence.

◆ EXIT

Exit the ALARM SETTING menu.

HOME SETTING

Users are able to set an operation mode to ensure constant monitoring; if the dome idles for a period of time, the pre-set function will be activated automatically, this is the HOME function. HOME function allows constant and accurate monitoring, to avoid the speed dome stops or missing events.

HOME SETTING	
HOME FUNCTION	OFF
SELECT MODE	PRESET
PRESET POINT	001
RETURN TIME	001
GO	ENTER
EXIT	YES

◆ **HOME FUNCTION**

The item is used to enable or disable the HOME function.

◆ **SELECT MODE**

Select one of the modes that the dome should execute when HOME function is enabled and the RETURN TIME is up. The options are <AUTOPAN>, <SEQUENCE>, <CRUISE> and <PRESET>.

◆ **PRESET**

Select a preset point where the speed dome should go when alarm pin is triggered.

SEQUENCE

Select a sequence line that the speed dome camera should execute when alarm pin is triggered. The Sequence line should be defined prior in SEQUENCE setup menu.

AUTOPAN

Select an auto-pan line that the speed dome camera should execute when alarm pin is triggered. The Auto-pan line can be defined in setup AUTOPAN setup menu.

CRUISE

Select a cruise line that the speed dome camera should execute when alarm pin is triggered. The Cruise line can be defined in CRUISE setup menu.

◆ **RETURN TIME**

The speed dome starts to count down RETURN TIME when the dome idles, and will execute the SELECT MODE function if the return time is up. The RETURN TIME ranges from 1 to 128 minutes.

◆ **GO**

If HOME function is enabled, the users are allowed to execute HOME function manually by selecting this item.

◆ **EXIT**

Exit the HOME SETTING menu.

SEQUENCE

The function executes pre-positioning of the pan, tilt, zoom and focus features in a certain sequence for a camera. Before set up this function, users must setup at least two preset points.

SEQUENCE	
SEQUENCE LINE	1
SEQUENCE POINT	01
PRESET POSITION	001
SPEED	1
DWELL TIME	001
RUN SEQUENCE	ENTER
EXIT	YES

◆ **SEQUENCE LINE**

There are eight sets of sequence lines built in the speed dome camera. Using LEFT/RIGHT direction keys to select a line first and then set its sequence points.

◆ **SEQUENCE POINT**

Up to 32 points can be specified for each sequence line. The sequence points represent the orders of the preset points that the dome will automatically run, and the following setup items, PRESET POSITION, SPEED, and DWELL TIME, are related to this item.

◆ **PRESET POSITION**

Users can assign a specific preset position to the selected sequence point with this item.

◆ **SPEED**

Users can set the Speed that the dome goes to the next sequence point, and setup speed range is from 1 ~ 15. Refer to below table for more information.

	PAN (degree/sec.)	TILT (degree/sec.)
Speed 1	10	8
Speed 2	23	12
Speed 3	35	22
Speed 4	45	30
Speed 5	55	40
Speed 6	65	50
Speed 7	75	58
Speed 8	185	185
Speed 9	205	210
Speed 10	225	240
Speed 11	250	275
Speed 12	280	305
Speed 13	320	335
Speed 14	365	365

Speed 15	400	400
-----------------	-----	-----

◆ **DWELL TIME**

The DWELL TIME is the duration time that the speed dome will stay at the sequence point, and the range is from <0> to <127> seconds. The speed dome will go to the next sequence point when the DWELL TIME is up. If the setting is <0>, the speed dome will stay at this sequence point until users manually move the speed dome.

◆ **RUN SEQUENCE**

User can command the speed dome camera to run the selected Sequence line manually.

◆ **EXIT**

Select the item to exit the SEQUENCE menu.

AUTOPAN

Auto-pan means rotating or scanning side-to-side motion by a speed dome camera to view an area horizontally. The parameters can be set on this page.

AUTOPAN	
AUTOPAN LINE	1
START POINT	TO FIND
END POINT	TO FIND
DIRECTION	RIGHT
SPEED	1
RUN AUTOPAN	ENTER
EXIT	YES

◆ **AUTOPAN LINE**

There are four sets of auto-pan lines built in speed dome camera. Users are able to command the speed dome camera to do continuously panning without limit by setting the start point the same as endpoint.

◆ **START POINT**

Follow the description to set the start position of the AUTOPAN path.

1. Move the cursor to <START POINT> and press <ENTER> while <TO FIND> item flashes, the item will turn <TO SAVE> automatically.
2. Move the speed dome to a desired position and press <ENTER> to save the position as the start point; the cursor will move to <END POINT> automatically. Ensure to set the end

point to complete the auto-pan setting.




NOTE: The tilt and zoom value of the start point will be recorded and fixed for the selected auto-pan line.

◆ **END POINT**

Users are able to set the end point after the start point is defined. Pan the dome to another position and press <ENTER> to save the position as the end point.

◆ **DIRECTION**

The item is for setting the AUTOPAN direction of speed dome camera. The speed will start to pan clockwise from the start point to the end point if your selection is <RIGHT>, and then return to the start point. The speed dome will start to pan anti-clockwise from the start point to the end point if your selection is <LEFT>. Refer to below diagram.



◆ **SPEED**

The item is for defining the speed dome camera rotation speed while running auto-pan. The speed is adjustable from 1 to 4; refer to the table below for details.

	PAN (degree/sec.)
Speed 1	10
Speed 2	23
Speed 3	35
Speed 4	45

◆ **RUN AUTOPAN**

After the setting is completed, select this item to manually execute the Auto-pan function.

- ◆ **EXIT**
Exit the AUTOPAN setup menu.

CRUISE

A Cruise is a route of manual operations that can be stored and recalled to execute repeatedly. It can be formed of pan, tilt position.

CRUISE	
RECORD START	ENTER
RECORD END	ENTER
RUN CRUISE	ENTER
EXIT	YES

- ◆ **RECORD START**
Follow the description to record the CRUISE path.
 1. Rotate the speed dome camera to a desired view area. The percentage of the memory buffer will be displayed on the screen.



NOTE: Beware of the memory size when building the cruise path. After the percentage of the buffer becomes 100%, the path will not be recorded.

- ◆ **RECORD END**
The cursor will be moved RECORD END while building the cruise line; when the setting is completed, press <ENTER> to save the path.
- ◆ **RUN CRUISE**
After the setting is completed, select this item to manually execute the Cruise function.
- ◆ **EXIT**
Exit the CRUISE setup menu.

IR FUNCTION (Removable IR Cut)

With the IR cut filter, the speed dome can still catch clear image at night time or very dark light condition. During day time, the IR cut filter will be on to block the infrared light for clear image; during night time, the IR cut filter will be removed to catch infrared light to view images in black and white. Users are able to view color images when the IR function activated.

Refer to the description to operate the removable IR cut filter.

◆ **AUTO**

The internal circuit will automatically decide the occasion to remove the IR cut filter according to the value of light condition calculated by the internal light algorithm.

◆ **ON**

Select the item to remove the IR cut filter.

IR FUNCTION	
THRESHOLD	LOW
IR COLOR	COLOR
EXIT	YES

◆ **AUTO**

The internal circuit will automatically decide the occasion to remove the IR cut filter according to the image brightness level.

THRESHOLD

The speed dome will remove the filter immediately when the threshold value is reached. The threshold options are <LOW>, <MID> and <HI>. <LOW> threshold indicates a higher sensitivity and can improve the reliability of lens.

IR COLOUR

When IR function is enabled, the video output can be programmed as colour or B/W.

◆ **ON**

Select the item to remove the IR cut filter.

WDR SETTING

The Wide Dynamic Range function is especially effective in solving indoor and outdoor contrast issues to enhance better image quality and video performance. It enables the speed dome to catch detailed data from the dark part (Indoor) without any saturation from the bright part (Outdoor). The parameter of WDR function can be set on this page.



NOTE: The Backlight function will automatically turned off when the WDR function is enabled, because the WDR

function has better effect than the Backlight compensation.

WDR SETTING	
WDR SWITCH	OFF
WDR FUNCTION	AUTO
EXIT	YES

◆ **WDR SWITCH**

Enable or disable the WDR function with the item.

◆ **WDR FUNCTION**

The item is used to define the WDR function mode.

AUTO

If select <AUTO>, the speed dome camera operates the WDR function automatically.

MANUAL

Users are allowed to adjust WDR function manually by defining the RATIO LEVEL, SHUTTER SPEED and IRIS OFFSET value.

WDR MODE	
RATIO LEVEL	000
SHUTTER SPEED	000
IRIS OFFSET	000
EXIT	YES

◆ **EXIT**

Exit this setup menu.

PRIVACY

The Privacy Mask function aims to avoid any intrusive monitoring. Users can adjust the camera view position, and adjust the mask size and area. The speed dome camera will memorize the center of the selected view as an original point, so it will be locked as users enter the Privacy Setup menu. Refer to the description for setting Privacy masks.



NOTE: The Image Flip function will be disabled automatically while the Privacy function is enabled.

PRIVACY	
PRIVACY SWITCH	ON
SHADE	GRAY
SET MASK	01
MASK CLEAR+RESET	01
MASK DISPLAY	FIRST
EXIT	YES

◆ **PRIVACY SWITCH**

The item is used to enable or disable masking function. Set this item to <ON> before configuring mask zone.

◆ **SHADE**

The colour of privacy mask can be selected through this item. The available colours are black, gray and white.

◆ **SET MASK**

After pressing <ENTER> on this item, speed dome will memorize this position as privacy mask position, up to 8 masks can be set. The model restricts the mask zones to be set too close with each other.

MASK01 MENU	
H CENTER	000
V CENTER	000
H SIZE	000
V SIZE	000
EXIT+SAVE	YES

H CENTER(000 ~ 256)

The original center of mask zone is the center of screen. User can move the center of mask zone to another position through adjust this value.

V CENTER(000 ~ 256)

The original center of mask zone is the center of screen. User can move the center of mask zone to another position through adjust this value.

H SIZE(000 ~ 127)

User can adjust the horizontal size of privacy mask through this item. Set the H and V size to 0 can also delete the selected mask.

V SIZE(000 ~ 127)

User can adjust the vertical size of privacy mask through this item. Set the H and V size to 0 can also delete the selected mask.

◆ **MASK CLEAR+RESET**

The item is used to clear the mask settings of the selected privacy mask. Select a mask and press <ENTER> to erase its configuration.

◆ **MASK DISPLAY**

This item is used to set the occasion to display privacy mask.

FIRST

If select this mode, the camera will detect the mask zone of the next preset position and display the mask in advance, then pan the speed dome to the preset point.

LAST

If select this mode, the camera will move the speed dome to the preset point, then display the mask zone.



NOTE: The available area for setting privacy mask is restricted within tilt angle 45°, and two mask zones are allowed to set in a view area.

◆ **EXIT**

Exit this page.

TIME FUNCTION

The item is used to set the TIME related parameters of the integrated high speed dome.

TIME SETTING	
TIME DISPLAY	OFF
SET YEAR	05
SET MONTH	10
SET DAY	02
SET HOUR	12
SET MINUTE	12
FXIT+SAVF	YES

◆ **TIME DISPLAY**

Select <ON> to display the Time information on screen, or <NO> not to display.

◆ **YEAR / MONTH / DAY**

The items are for setting up the system date.

◆ **HOUR / MINUTE**

This items are for setting up the system time.

◆ **EXIT+SAVE**

Exit this page.

EXIT OSD

To exit the OSD setup menu, users can select this item.

Product Specification

TCM-6630	
•Device	
Device Type	Speed Dome Camera
Image Sensor	Sony EXview HAD Interlaced Scan CCD
Sensor Size	1/4" (3.2 x 2.4 mm)
Horizontal Resolution	650 TVL
Day / Night	Yes
Minimum Illumination Color:	0.1 lux; B/W: 0.01 lux
Color to B/W switch	DSP based switch, configurable
Mechanical IR Cut Filter	Yes
IR Sensitivity Range	700 - 1100 nm
IR LED	No
Electronic Shutter	1/1 - 1/10,000 sec (NTSC/PAL)
•Lens	
Focal Length	Zoom, f3.4 - 122.4 mm / F1.6 - 4.5
Iris	Auto iris
Focus	Auto focus
Horizontal Viewing Angle	57.8° - 1.7°
•PTZ	
Zoom Ratio	36x optical; 12x digital
Zoom Speed	4 sec (1x to 36x) Manual
Manual Panning Speed	0.5° ~ 90° /s
Manual Tilting Speed	0.5° ~ 90° /s
Preset Panning Speed	5° ~ 400° /s
Preset Tilting Speed	5° ~ 400° /s
Panning Range	0° ~ 360° endless
Tilting Range	-10° ~ 190°
Control	Remote manual control; 256 preset points; 8 preset tours; auto scan
Preset Panning Accuracy	0.225°
Preset Tilting Accuracy	0.45°
Absolute Position	Yes
Protocol	DSCP, Pelco P, Pelco D, AD422, Philips, Kalatel, VCL, JVC, etc.
•Video	
Compression	H.264, MPEG-4 SP, MJPEG
Maximum Frame Rate vs. Resolution	30 fps at 720 x 480 (Full D1, NTSC); 25 fps at 720 x 576 (Full D1, PAL) 30 fps at 352 x 240 (CIF, NTSC); 25 fps at 352 x 288 (CIF, PAL) 30 fps at 160 x 112 (QCIF, NTSC); 25 fps at 176 x 144 (QCIF, PAL)
Multi-Streaming	Simultaneous dual streams based on two configurations
Bit Rate	28 Kbps - 6 Mbps (per stream)
Bit Rate Mode	Constant, Variable
S/N Ratio	More than 50 dB
Image Enhancement	Wide dynamic range; Backlight compensation; White balance: automatic, predefined and manual;
Privacy Mask	16 configurable regions
Text Overlay	User defined text on video
Image Orientation	Image flip and mirror

•Audio	
Compression	8 kHz, Mono, PCM, 16 bit encoding
Audio-In	3.5 mm Phone Jack
Audio-Out	3.5 mm Phone Jack
•Network	
Protocol & Service	TCP, UDP, HTTP, HTTPS, DHCP, PPPoE, RTP, RTSP, IPv6, DNS, DDNS, NTP, ICMP, ARP, IGMP, SMTP, FTP, UPnP
Security	IP address filtering; HTTPS encryption; Password protected user levels; IEEE
•Alarm	
Alarm Trigger	Video motion detection (3 regions); External device through digital input
Alarm Response	Notify control center; Go to PTZ preset point or preset tour; Change camera settings; Command other devices; E-mail notification with snapshots; Upload video, snapshot to FTP server; Activate external device through digital
•Interface	
Analog Video Output	1, CVBS, 1.0Vp-p with 75 Ω BNC connector
Digital Input	8, terminal block
Digital Output	1, terminal block
•General	
Power Source / Consumption	AC 24V / 65 W (heater on)
Weight	5800 g (12.9 lb)
Dimensions (Ø x H)	172 mm x 302.5 mm (6.7" x 11.9"); 190 mm x 302.5 mm (7.5" x 11.9") with
Environmental Casing	Weatherproof (IP66 rated); Transparent dome cover
Mount Type	Pendant, Wall, Corner, Pole
Operating Temperature	-45 °C ~ 50 °C (-49 °F ~ 122 °F)
Operating Humidity	10% ~ 85% RH
Approvals	Camera: CE, FCC, IP66; Adapter: CE, TUV-GS, UL, RCM, CCC
•Integration	
Unified Solution	Fully compatible with ACTi software
ISV Integration	Software Development Kit (SDK) available
Firmware Access Browser	Microsoft Internet Explorer 6.0 or newer

4. Accessing Camera


If you have DHCP server / router in your network:

Many network server / routers are able to automatically provide IP addresses through DHCP. If you are using such a network, just plug in your computer and IP Camera into the network and your IP device will acquire network address by itself. Find and access the device with our IP Utility program. You may download it at:

http://www.acti.com/product/detail/Software/ACTi_Utility_Suite

If you do **NOT** have DHCP server / router in your network:

1. Configure your PC to use the same subnet by changing your PC's IP address to the subnet with prefix 192.168.0.XXX. The last number should be anything from 1 to 254 except 100 and other occupied IP addresses. Subnet mask should be 255.255.255.0.
2. **The default IP used by this device is 192.168.0.100. Please make sure your PC is NOT using this address and that no two equipments use the same IP address in the network.**
3. Change your IP address by going to Control Panel ->Manage Network Connections -> Right click on the connection to change -> Option -> TCP/IP IPv4 Properties.



Please set the settings as below.

-
- IP address: 192.168.0.xxx
- Subnet mask: 255.255.255.0


(NOTE: xxx should be a number from 1 to 254 except 100, which is used by the IP device. Please also make sure that no two equipments use the same IP address in the same network..)

4. Open Internet Explorer (Version 6.0 or above) , and type in the Default IP:

192.168.0.100

5. When you see the login window, please input default user and password:

Default User: Admin Password: 123456




6. After logging in, you will see the video from camera. To go to the main menu, click the "Setup" button on the top left.



If you are using a single camera, this is enough to access the device.


If you are using multiple devices, you need to change the current device to another unused IP address, so that when the next device is connected to the network, no two devices use the same IP. Please perform the following steps.

7. Go to IP Settings -> Connection Type
8. Change the IP mode to Static.
9. Change the IP to 192.168.0.101 or any other unused IPs. Do NOT use the PC's IP address or 192.168.0.100.). If this is not the first device you add to the network, please also avoid other devices' IPs.



10. Click “Apply”

11. Please go to System -> Save & Reboot, and click “Apply”. Internet Explorer will close after a few seconds. This is normal.



12. Wait for 30 seconds, and open IE again to connect to the **new IP**. (In this example, 192.168.0.101). For the second device or more you add into the network, please type the correct IP.

13. Adjust the default Video setting by going to Video & Audio -> Video

